

NON-ENCLOSED ELECTRONIC

Transformers

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

PRODUCT DESCRIPTION

Low Voltage electronic transformer designed to be used as a replacement part for factory installed transformers or installed in a properly listed enclosure.

FEATURES

- 1W minimum load
- All connections must be made in an enclosure for proper installations
- Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer.

SPECIFICATIONS

Construction: Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

Output: 12V

Frequency: 20khz

Details: In the case of a system overload or short circuit the transformer will revert to a "hold" position and then automatically reset the system when the problem is solved. System protection is designed to last several hours.

Standards: UL recognized component part.

ORDER NUMBER

Model	Voltage	Wattage	Min Load	L	W	H	Class 2	Auto Reset
EN-1260-R2*	120VAC	12VAC 60W	1W	2 ³ / ₈ "	1 ³ / ₈ "	1"	Yes	Yes
EN-1260-R-AR	120VAC	12VAC 60W	1W	2 ³ / ₈ "	1 ³ / ₈ "	1"	Yes	Yes
EN-1275-R-AR	120VAC	12VAC 75W	1W	2 ³ / ₈ "	1 ³ / ₈ "	1"	No	Yes
EN-12100-R-AR	120VAC	12VAC 100W	1W	3 ¹ / ₂ "	1 ¹ / ₂ "	1 ¹ / ₈ "	No	Yes
EN-12150-R-AR	120VAC	12VAC 150W	1W	3 ¹ / ₂ "	1 ¹ / ₂ "	1 ¹ / ₈ "	No	Yes

*U.L. Listed Class 2 Component

ACCESSORIES

Model		L	W	H
MTB-01	Multiple Terminal Block	3 ¹ / ₄ "	1 ³ / ₄ "	7 ⁸ / ₈ "
METB	Enclosure & Connection Box	6 ⁵ / ₈ "	1 ⁵ / ₈ "	1 ¹ / ₈ "

waclighting.com

Phone (800) 526.2588

Fax (800) 526.2585

Headquarters/Eastern Distribution Center

44 Harbor Park Drive

Port Washington, NY 11050

Central Distribution Center

1600 Distribution Ct

Lithia Springs, GA 30122

Western Distribution Center

1750 Archibald Avenue

Ontario, CA 91760