INSTALLATION AND SAFETY INSTRUCTIONS

FOR YOUR SAFETY WARNING

BE SURE THE ELECTRICITY TO THE WIRES YOU ARE WORKING ON IS SHUT OFF; EITHER THE FUSE IS REMOVED OR THE CIRCUIT BREAKER IS SHUT OFF. GENERAL You don't need special tools to install this fixture. Be sure to follow the steps in the order given. Under no circumstances should a fixture be hung on house electrical

wires, nor should a swag type fixture be installed on a ceiling which contains a radiant type heating system. Read instructions carefully. If you are unclear as to how to proceed, consult a qualified electrician. NOTE: Proper wiring is essential for the safe operation of this fixture.

GENERAL

You don't need special tools to install this fixture. Be sure to follow the steps in the order given. Under no circumstances should a fixture be hung on house electrical wires, nor should a swag type fixture be installed on a ceiling which contains a radiant type heating system. Read instructions carefully. If you are unclear as to how to proceed, consult a qualified electrician. **NOTE:** Proper wiring is essential for the safe operation of this fixture.

FIXTURE ASSEMBLY

Carefully remove the fixture from the carton and check that all parts are included as shown in figure. Be careful not to misplace any of the screws or parts, which are needed to install this fixture.

INSTALLATION

IMPORTANT: Do not attach fixture directly to outlet box.

- **STEP 1:** Thread mounting screws (A) into the match holes of Circular strap (B).
- **STEP 2:** Secure circular strap (B) to outlet box with outlet box screws (C).

GROUNDING INSTRUCTIONS

STEP 1: Insert the green grounding screw into the hole with two raised dimples on the mounting bar. Wrap the ground wire from the fixture (if supplied) around the green grounding screw, then connect it to ground wire from the outlet box (if not fixed on the outlet box) using a wire connector (not supplied). If ground wire from the fixture is not supplied, wrap the ground wire (if not fixed on the outlet box) from the outlet box around the green grounding screw and tighten it.

NEVER CONNECT GROUND WIRE TO BLACK OR WHITE POWER SUPPLY WIRES.

STEP 2: Take note of the color of the wire(s) on your fixture. Identify which group your fixture wire(s) falls into and connect the wires according to the directions below:

GROUP A: Connect to Black GROUP B: Connect to White House Wire House Wire BLACK WHITE *PARALLEL WIRE (round & *PARALLEL WIRE (square & ridged) WHITE OR GREY WITH WHITE OR GREY WITH TRACER BROWN GOLD OR BLACK BROWN, GOLD OR BLACK WITH TRACER		
BLACK WHITE *PARALLEL WIRE (round & *PARALLEL WIRE (square & ridged) WHITE OR GREY WITH WHITE OR GREY WITH TRACER BROWN GOLD OR BLACK	GROUP A: Connect to Black	GROUP B: Connect to White
*PARALLEL WIRE (round & *PARALLEL WIRE (square & smooth) WHITE OR GREY WITH WHITE OR GREY WITHOUT TRACER TRACER BROWN GOLD OR BLACK BROWN, GOLD OR BLACK	House Wire	House Wire
smooth) ridged) WHITE OR GREY WITH TRACER TRACER BROWN GOLD OR BLACK	BLACK	WHITE
WHITE OR GREY WITH WHITE OR GREY WITHOUT TRACER TRACER BROWN GOLD OR BLACK BROWN, GOLD OR BLACK	*PARALLEL WIRE (round &	*PARALLEL WIRE (square &
TRACER TRACER BROWN GOLD OR BLACK BROWN, GOLD OR BLACK	smooth)	ridged)
BROWN GOLD OR BLACK BROWN, GOLD OR BLACK	WHITE OR GREY WITH	WHITE OR GREY WITHOUT
	TRACER	TRACER
WITHOUT TRACER WITH TRACER	BROWN GOLD OR BLACK	BROWN, GOLD OR BLACK
WITHOUT HOUSER	WITHOUT TRACER	WITH TRACER

*NOTE: When parallel wire (SPT-I & SPT-2) is used, the tracer wire is square shaped or ridged and the less tracer wire is round in shape or smooth (seen best when viewed from wire end.) **STEP 3:** Take your fixture wire(s) from group A and place evenly against the black wire from the outlet box. Do NOT twist wires together before using wire connectors.

- **STEP 4:** Fit a wire connector (not supplied) over the wires and screw the connector clockwise until you feel firmness.
- **STEP 5:** Try gently to pull the connector off the wires. If you can pull the connector off, carefully re-do steps 3 and 4 as above, and check again for a firm connection.
- **STEP 6:** Connect the fixture wire from group B to the white wire from the outlet box in the same manner. Make sure no bare wires can be seen outside wire connectors.

FINAL ASSEMBLY


- STEP 1: After wires are connected, tuck them carefully inside outlet box. Raise canopy (D) allowing for the mounting screws (A) to protrude through the hole on canopy (D), then secure with ball nuts (E).
- STEP 2: Install light bulb. (Please do not exceed the maximum capacity recommended on the socket.)
- STEP 3: Raise glass (H) allowing for ball screws (G) to protrude through the hole on glass (H),then secure with ball screws (G) to socket cap (F) iron prop.

CLEANING

To clean, wipe fixture with a soft cloth. Clean glass with a mild soap. Do not use abrasive materials such as scouring pads or powders, steel wool or abrasive paper.

ORDERING PARTS

Keep this sheet for future reference, and in case you need to order replacement parts. Be sure to use exact wording from illustration when ordering parts.



Line art shown may not exactly match the fixture enclosed. However, the installations do apply to this fixture. ITEM NO: 471-1S 471-2V 471-3V 471-4V 471-5V