

Assembly & Installation Instructions for: 031322-010-FR001_2-Light Wall Sconce

At Home In Any Environment




crystal ornamental

Customer Service :(702)361-4345,(800)525-2655,customer.service@kalco.com

WARNING - TO REDUCE THE RISK OF FIRE OR INJURY:

- 1.If you are unfamiliar with electrical wiring, call a qualified electrician to install this unit .More than one person may be necessary to install fixture ,make sure you have enough qualified help.
- 2.Turn off the power to the fixture's circuit at the service panel. Use a voltage detector to verify that the power is off.
- 3.DO NOT install bulb which exceeds the maximum wattage specified on the socket label.

Fixture Assembly





Assembly & Installation Instructions for: 031322-010-FR001 2-Light Wall Sconce

At Home In Any Environment

Customer Service :(702)361-4345,(800)525-2655,customer.service@kalco.com

Fixture Assembly

- Step 5. Fasten 2 (state specification of screw) into mounting plate so that they extend away from wall when mounting plate is installed
- Step 6. Attach the mounting plate to outlet box with screws
- Step 7. Refer to wiring diagram. Splice the ribbed side of fixture cord to the white supply wire from outlet box with wire connector. Splice the smooth side of the fixture cord to black supply wire from outlet box with wire connector
- Step 8. Carefully tuck in all wires Attach the back plate with the mounting screw on the crossbar.Secure fixture with shell knobs.

